

1-Channel RF Receivers



Model Numbers

SK-910RBQ
315MHz

SK-910RB-4Q*
433.92MHz

Specifications

Model	SK-910RBQ	SK-910RB-4Q
Number of channels	1	
Operating frequency	315MHz	433.92MHz
Memory capacity	15 Transmitter button codes	
Operating voltage	11~24 VAC/VDC	
Current draw	30mA@12VDC	
Relay rating	NO/NC/COM Relay, 10A@24VDC/120VAC	
Dimensions	3 1/8" x 2 9/16" x 1" (80x65x25 mm)	

Features

- Five programmable relay output modes: 4-second momentary, 1-second momentary, toggle, latch, and validity
- Control garage doors, gates, house lights, alarm panels, or other devices via remote
- LED indicates RF transmission programming options and output modes
- One-button programming - no need to cut jumpers

Accessories

SK-91ERSD

Extended range antenna for 315MHz receivers

SK-93ERSD

Extended range antenna for 433.92MHz receivers



Miniature 1-Channel RF Receivers



Model Numbers

SK-910RAQ
3A relay, 11~24 VAC/VDC

SK-910RAVQ
5A Transistor ground, 3~13.8 VDC

Specifications

Model	SK-910RAQ	SK-910RAVQ
Number of channels	1	
Operating frequency	315MHz	
Memory capacity	15 Transmitter button codes	
Operating voltage	11~24 VAC/VDC	3~13.8 VDC
Current draw	50mA@12VDC	15mA@12VDC
Output	NO/NC/COM Relay, 3A	Transistor ground, 5A
Dimensions	3 3/16" x 2 9/16" x 3/4" (80x65x19 mm)	

Features

- Control garage doors, gates, house lights, alarm panel, or other devices via remote
- Small size
- LED indicates RF transmission programming options and output modes

Accessories

SK-91ERSD

Extended range antenna (SK-910RAQ only)



*Special order item. Please contact SECO-LARM for details.